



*Your Lighting Solution Partner*



# MAGUS

## Art-Net RDM & DMX Player

Zenopix Magus provides automatic addressing of RDM/DMX decoders and control of fixtures via DMX, thanks to the RDM/DMX protocol.

[zenopix.com](http://zenopix.com)





## Magus Product Description

- Converts Art-Net packets into RDM and DMX outputs.
- Provides control by transmitting ArtNet RDM and DMX data to connected devices.
- Provides the capability to address, read sensor data, and control of RDM-supported lighting devices,
- Controls up to 2048 RDM and DMX devices with two output ports.
- Works in conjunction with the free Zenopix Explorer RDM addressing and monitoring software.

## Magus Technical Specifications

|                                 |                                   |
|---------------------------------|-----------------------------------|
| <b>Input Voltage Range</b>      | 12-24VDC (Terminal)               |
| <b>Power Consumption</b>        | <5W (Normal Operating Conditions) |
| <b>Network Protocol</b>         | Art-Net RDM/DMX                   |
| <b>RDM In/Out Ports</b>         | 2 x 1024 Channel                  |
| <b>Output Ports Type</b>        | 3Pin, 5.08 Terminal               |
| <b>Ethernet</b>                 | 1x RJ45, 10/100Mbit/s             |
| <b>USB</b>                      | 1x USB 2.0 Type B port            |
| <b>Status LEDs</b>              | 2 Pieces                          |
| <b>Case</b>                     | Plastic                           |
| <b>Dimensions</b>               | 105 x 91 x 58.5 mm - Rail Type    |
| <b>Temperature and Humidity</b> | Operating: 5°C - 65°C / %20 RH    |
|                                 | Storage: -15°C - 75°C / %70 RH    |
| <b>Protection</b>               | IP-20                             |
| <b>Mounting Type</b>            | Wall / Rail Mounting              |



*Zenopix is an R&D, manufacturing, and technology company deeply specialized in lighting control systems, with nearly 20 years of extensive experience in electronics and software.*

+90 (312) 911 70 17 

info@zenopix.com 

zenopix.com 

Söğütözü Mah. Söğütözü Cad.   
Koç Kuleleri A Blok No:2A/13 Çankaya/Ankara